

Step by Step Instructions

NZW37 – 2 Channel Smart Outlet

**** For General Z-Wave HUB Users ****

Please note: the NZW37 smart plug has only been verified to FULLY function on the following HUBS/Gateways:

SmartThings, Wink, Vera (UI7), Staples Connect, HomeSeer

Make sure your HUB/Gateway supports multi-channel Z-Wave Devices

– Step 1 –

Gather Your Materials & Find an Appropriate Outlet

Materials Needed:

- Grounded Outlet
- Cell Phone or Computer to sync your device
- Z-Wave enabled HUB/Gateway

Locate an indoor outlet which is grounded and within the recommended distance (less than 100ft) from your Z-Wave Hub/Gateway.

Walls, furniture, and other obstructions may affect the communication between the Plug-In Module and your Hub/Gateway, so please keep this in mind when selecting our location.

Please contact us if you have any issues: contact@inovelli.com

-Step 2-

Plug In Lamp(s)/Appliance(s)

Before plugging in your module, please plug in the device(s) you are looking to control. In addition, make sure that both devices together do not equal more than 10 Amps.

Again, please make sure you have a Z-Wave compatible HUB/Gateway, or this will not work.

Note: It is not recommended plugging in space (electric) heaters, or any other appliances that may present a hazardous condition due to unattended, unintentional, or automatic power control.

-Step 3-

Plug In the Module & Exclude (Optional)

You are now ready to plug in your module and start to sync to your selected Z-Wave Hub/Gateway.

Before we start the official syncing (including) process, we are going to go over how to exclude a device. This step is optional, but we like to do it with any new Z-Wave device we get/test, just to make sure. The excluding process is like a reset, and it's helpful if you bought the device used, or if there is an issue with your HUB/Gateway. Plus, it doesn't hurt!

Excluding Steps:

- Start the Exclusion process on your Hub
- Push on the Middle Button on the front of your NZW37 3-5 times within 3 seconds
- You should now see that your device is excluded – please move on to Step 4

-Step 4-

Adding (Including) to the Network & Completing the Setup Process

Once you've finished the Exclusion Process (or if you've skipped it) it's time to include your Z-Wave device to your network.

PAIRING ON OTHER Z-WAVE HUBS/GATEWAYS:

- Start the inclusion process on your phone
- Press the Middle Button on the front of your NZW37 3-5 times within 3 seconds to activate inclusion
- You should now see that your device is detected
- Go ahead and configure the device! Congratulations!