

Step by Step Instructions

NZW37 – 2 Channel Smart Outlet

**** For Samsung SmartThings ****

– Step 1 –

Gather Your Materials & Find an Appropriate Outlet

Materials Needed:

- Grounded Outlet
- Cell Phone or Computer to sync your device
- Z-Wave enabled HUB/Gateway

Locate an indoor outlet which is grounded and within the recommended distance (less than 100ft) from your Z-Wave Hub/Gateway.

Walls, furniture, and other obstructions may affect the communication between the Plug-In Module and your Hub/Gateway, so please keep this in mind when selecting our location.

Note: Currently, we only have full videos for SmartThings. But since our product is Z-Wave Plus certified, it will work with all Z-Wave Hub/Gateways, unless the manufacturer has chosen to only work with select companies. We've tested and confirmed that this plug works with Vera and Wink.

-Step 2-

Plug In Lamp(s)/Appliance(s)

Before plugging in your module, please plug in the device(s) you are looking to control. In addition, make sure that both devices together do not equal more than 10 Amps.

Again, please make sure you have a Z-Wave compatible HUB/Gateway, or this will not work.

Note: It is not recommended plugging in space (electric) heaters, or any other appliances that may present a hazardous condition due to unattended, unintentional, or automatic power control.

-Step 3-

Plug In the Module & Exclude (Optional)

You are now ready to plug in your module and start to sync to your selected Z-Wave Hub/Gateway.

Before we start the official syncing (including) process, we are going to go over how to exclude a device. This step is optional, but we like to do it with any new Z-Wave device we get/test, just to make sure. The excluding process is like a reset, and it's helpful if you bought the device used, or if there is an issue with your HUB/Gateway. Plus, it doesn't hurt!

Excluding Steps:

- Open up your SmartThings app
- Click on the three arrows in the top right of your app (menu)
- Click on, "Hub is Online"
- Click on, "Z-Wave Utilities"
- Click on, "General Device Exclusion"
- Push on the Middle Button on the front of your NZW37 3-5 times within 3 seconds
- You should now see that your device is excluded – please move on to Step 4

-Step 4-

Adding (Including) to the Network & Completing the Setup Process

Once you've finished the Exclusion Process (or if you've skipped it) it's time to include your Z-Wave device to your network.

Including Steps:

- If you've excluded, press the back button, and then the "x" until you are at the screen where you see, "Add a Thing"
- Press, "Add a Thing" at the bottom of the screen
- Click on, "Start Looking for Things"
- Press the Middle Button on the front of your NZW37 3-5 times within 3 seconds to activate inclusion
- You should now see that your device is detected

Setup After Inclusion

- After your device was detected, press, "Tap to Configure"
- Name your device and click, "Next" (unless you want to assign to a room)
- Now, you should be on the, "Top SmartApps" page
- Scroll to the bottom and click, "Multi-Channel Control"
- Select the device you'd like to use (the device you just set up – also, you can skip, "Assign a Name" and "Set for Specific Mode(s)) and click, "Done"
- You should see a green box that your device is now connected
- Click, "Done" again
- You should see another green box that says your device is now connected

On your, "My Home" screen under, "Things", you should see your switch, along with two end-points. Feel free to change the end-point names to whatever you have plugged into it.

To change the endpoint names, do the following:

- Click on, "Switch Endpoint 1"
- Click on the gear icon in the top right of the screen
- Click on, "Edit Device"
- Name it whatever you'd like

Repeat the above for, "Switch Endpoint 2" and you're all set. Congratulations!